

## SUPRAPAQ TH76

# TRANSMITTER | 10 BUTTONS WITH DISPLAY

**Compatible with Panther and Puma  
Buttons**

**Display**

**Frequency**

**Radio frequency band**

**Frequency management**

**Radio frequency output power**

**Radio communication**

**Battery**

**Number of batteries**

**Charging**

**Weight**

**Dimensions (w x h x d)**

**Protection**

**Operating temperature**

**Charging temperature**

**Safety level**

**On/off switch**

**Smartphone Connectivity**

**Smartphone App FieldManager™**

**RFID**

**Easy plug-in abilities**

**Acceleration sensor**

**Buzzer**

Yes

10 2-step buttons

Yes

2,4 GHz, 16 channels

2405 - 2480 MHz

Direct Sequence Spread Spectrum (DSSS)

EIRP: <12dBm (15.85mW) FCC+IC Max EIRP: <18dBm (63mW)

Duplex when using Puma protocol, simplex when using Panther protocol

3.7 V/ 2000 mAh Li-ion, rechargeable

1 changeable

12-36V DC

328 grams, without battery

79x210x42 mm

IP65

-20 to +55 degrees Celcius

+10 to +35 degrees Celcius

Ple, CAT4, SIL3 on stop function

No

Yes IEEE 802.15

Yes (Android/iOS)

Yes

Yes

Yes

Yes

*Changes and errors reserved.*

PLEASE VISIT OUR WEBSITE FOR OUR WORLDWIDE LOCATIONS

**teleradio.com**

**SAFE • SMART • STRONG**

**SupraPAQ TH76**



**NEW**  
**SUPRAPAQ TH76**  
with FieldManager™  
smartphone App  
connectivity

**TECHNICAL DATA**

AN **ALLGON®** COMPANY